

Temporary Power Distribution

SM5 (PSOA) FOR CONSTRUCTION SITE USE – PORTABLE SOCKET OUTLET ASSEMBLY, 5 X 10 AMP WITH 10 AMP PLUG



APPLICATIONS

A safe and portable socket outlet assembly (PSOA) for use on construction sites.

CONSTRUCTION

- 5 x 10A sockets: 250V, 50Hz, IP66, RCBO protected
- 10A industrial plug on 1.8m heavy duty lead (AS/NZS 3191)
- Supply – 10A, 230V – single phase + N + E
- RCBO - 2 pole 10A 30mA 230V
- IP65 enclosure
- 3.5kg with cable and plug
- Meets requirements of AS/NZS 3012
- Dimensions – 325mm (L) x 295mm (H) x 270mm (W)

PRODUCT FEATURES

- Bright, visible and safe
- Weathertight: IP65 enclosure + IP66 outlets
- Robust and rugged enclosure with durable handle
- Overall RCBO protection
- Tested and certified
- Ground clearance

Product Code	Cable Size (m)	Supply Power	Socket Outlets
SM5	1.8	10A, 230V – single phase + N + E	5 x 10A, 250V, 50Hz, IP66 RCBO protected

SM6 (PSOA) – PORTABLE SOCKET OUTLET ASSEMBLY, 6 X 15 AMP OUTLETS WITH 10 AMP PLUG



APPLICATIONS

Residential and light commercial building sites.

CONSTRUCTION

- 6 x 15A sockets single phase 3P
- 10A industrial plug on 1.8m heavy duty lead (AS/NZS 3191)
- Frequency 50Hz
- Supply – 10A, 230V – single phase + N + E
- RCBO - 2 Pole 10A 30mA 230V
- IP44/IP65
- Specially blended polyethylene enclosure
- Meets the requirements of AS/NZS 3012:2010
- Dimensions – 412mm (L) x 280mm (H) x 268mm (W)

PRODUCT FEATURES

- 2 Year limited warranty
- Industrial lead and plug
- Stackable for storage and transportation
- 40mm ground clearance
- Third party tested and certified
- Impact resistant robust enclosure for outdoor use
- Assembled with standard industrial sockets allowing hassle free replacement
- Customisation available on request
- Assembled with trade tested components
- Designed for NZ & AU conditions

Product Code	Cable Size (m)	Supply Power	Socket Outlets	Weight (kg)
SM6	1.8	10A, 230V – single phase + N + E	6 x 15A single phase 3P	6

Powervos has taken every precaution to ensure accurate information on this data page, but accept no liability for any errors or omissions. Powervos reserves the right to modify specifications at any time.